

# COBRA 1



## SPECIFICATIONS

The Cobra 1 maintains efficient AC Emergency Power to operate all emergency lighting fixtures at "full-light" output, after the transfer is complete, providing superior dependability and security to commercial/industrial environments in a small footprint.

### POWER RATING

- 4.7 KW - 21 KW (or 4,700 Watts - 21,000 Watts) single phase output unit uses the latest DSP/PWM technology to provide the most advanced performance and reliability features

### INPUT

- 120V, 208V, 240V, 277V or 480V input 60Hz

### OUTPUT

- 120V, 240V, 277V, 480V, 120/240 or 120/277VAC
- Stand-by design is  $\geq 99\%$  efficient at 100% linear load

### BATTERIES


- Sealed, maintenance-free, lead calcium (AGM) batteries
- 10-Year prorated warranty
- *DSP/PWM Smart Battery Monitoring System* is **TEMPERATURE COMPENSATED** maintaining maximum runtime and battery life
- Microprocessor controlled recharge and DSP/PWM overcharge protection standard

### LAMPS AND LOADS

- Emergency power provides **FULL LIGHT OUTPUT** from all lamps and fixtures for the entire runtime
- Operates fluorescent, compact fluorescent, incandescent, quartz, LED and other lamp types
- Standard or electronic ballasts, dimming devices or panels, sensors and most control equipment
- Standard or LED Exits and other safety equipment

### CODES

- UL 924, UL 1778, meets NFPA 101, NFPA 70, NEC and OSHA standards
- Cities of Chicago and New York approved
- Complies with the Buy American Act



Catalog Number	
Project	Notes
Signature	Date

## 4.7 KW - 21 KW

### Single Phase

### Stand-By Emergency Lighting and Power Systems



### PROTECTION

- Provides overload, surge and undervoltage protection using DSP/PWM technology and Envoy *Watchdog Software* to protect system performance and reliability
- Transfer in 16msec - 60msec

### DIAGNOSTICS AND MAINTENANCE

- DSP/PWM technology and Envoy *Watchdog Software* provides complete self diagnostic capabilities and LED Monitoring
- Informative advanced Display and Alarms keep you in control of your emergency lighting environment 24/7
- Automatically performs periodic self-tests ensuring a safely lighted environment *prior* to an emergency
- Single point of testing instead of multiple testing points with battery packs

### CABINET

- Modular design enables flexible installation
- Forced air cooling for maximum reliability
- Systems up to 14 KW are self contained; larger systems require external battery cabinet(s)

### INSTALLATION

- Modular design and small footprint allow easy installation in electrical closet or other convenient locations
- Phone assisted factory start-up standard for all systems
- Extended warranty available

### SPECIAL APPLICATIONS

- Envoy offers numerous UL924 optional devices to meet unusual or difficult application parameters
- ECM - Environmental Circuit Module allows fixtures and lamps on the emergency circuit(s) to be operated by normal switching and/or dimming devices in NON-emergency conditions
- Dimming Panel Interface allows use with emergency lights controlled by common dimmer panel

### WARRANTY

- 1-Year full warranty on system electronics
- Battery warranty 1-year with 9-years pro-rated
- System 1-year on-site warranty labor with Envoy phone assisted start-up
- 5-Year powertrain warranty
- Maintenance contracts available



# COBRA 1



Cobra 1 Series	Power Rating	UPS			Battery			Weight (combined)	British Thermal Unit	Battery Type	Voltage (VAC)		Output Protection	Safety Approvals
		Cabinet Dimensions			Cabinet Dimensions						Input	Output		
CO1	KVA/KW	W	H	D	W	H	D	(lbs)	BTU's	Sealed, Maintenance free (AGM) lead calcium	Select	Select	Input and output circuit breakers standard	UL924 UL1778 NFPA 101 NFPA 70 NEC
	4.7	42"	71"	22.5"	not required			1200	159.8		120,	120,		
	5.25	42"	71"	22.5"	not required			1200	178.5		208,	277,		
	7.0	42"	71"	22.5"	not required			1450	238		240,	480,		
	8.0	42"	71"	22.5"	not required			1450	272		277	120/240		
	10.0	42"	71"	22.5"	not required			1820	340		or	120/277		
	12.0	42"	71"	22.5"	not required			2210	408		480	120/277		
	14.0	42"	71"	22.5"	not required			2550	476					
	18.0	42"	71"	22.5"	42"	71"	22.5"	3750	612					
	21.0	42"	71"	22.5"	42"	71"	22.5"	4375	714					

The Cobra 1 provides the simplicity and reliability that is critical when providing an alternative source of power to any environment. Easy installation ... "simplicity" ...connect the CO1 to the emergency circuit(s) and everything is backed up... "reliability" ...during a power outage. All lighting connected to the CO1 will simply continue to operate at **"full light output"** once the transfer is complete. Envoy Watchdog© software keeps your environment safe while self-diagnostics help maintain equipment to a high standard. Superior surge suppression assures the highest quality of power being delivered to all loads, all the time.

We sincerely hope you never experience a real emergency, but if you do, you deserve the **security, safety and peace of mind** that the Cobra 1 from **Envoy** ensures.

## ORDERING INFORMATION

Choose the bold face catalog nomenclature that best suites your needs.

Write them on the appropriate line. Order accessories as separate catalog number.

Example:

**CO1 - 8.0 - 120/277 - ECM277/3 OCB/277/3/20/1**

Description of example:

(8.0 KW, 120 Voltage In, 277 Voltage Out, 3 277V Environmental Control Modules, 3 Output 277 Voltage Circuit Breakers at 20amps, 2 pole)

CO1				
FAMILY	POWER RATING	VOLTAGE <sup>1</sup>	OPTIONS	TIME <sup>3</sup>
	<b>KW</b>	<b>Input/Output</b>	<b>Input/Output</b>	
	4.7	120/120	240/120-240	<b>ECM120</b> - 120V Environmental control module <sup>2/qty</sup>
	5.25	120/277	240/120-277	<b>ECM277</b> - 277V Environmental control module <sup>2/qty</sup>
	7.0	120/480	277/120	<b>NOF</b> - Normally OFF output circuit/voltage/qty/pole
	8.0	120/120-240	277/277	<b>NOH</b> - Normally OFF "Hold ON" voltage/qty/pole
	10.0	120/120-277	277/480	<b>OCB</b> - Output circuit breakers / voltage / quantity /amps/pole
	12.0	208/120	277/120-240	<b>EPO</b> - Emergency power off
	14.0	208/277	277/120-277	<b>RSSP</b> - Remote Indicator Panel
	18.0	208/480	480/120	<b>SNMP</b> - SNMP Card
	21.0	208/120-240	480/277	<b>FC</b> - Form C Contacts
		208/120-277	480/480	<b>SRB</b> - Seismic rated bracket
			240/120	<b>STU1</b> - Onsite start-up
			240/277	<b>IDB</b> - Internal dimmer bypass
			240/480	<b>EMB</b> - External maintenance bypass switch
				<b>EW</b> - Extended warranty
				<b>FT</b> - Fast transfer
				Minutes
				5
				10
				15
				20
				25
				30
				45
				60
				90 (Standard)
				120
				180
				240

### NOTES:

1-Consult factory for other voltage requirements.

Special voltages may effect the weight, size and number or cabinets.

2-One ECM is used per switching device or circuit.

3-Consult factory for other run times.

Specifications subject to change without notice.

